

# Multilayer Ferrite Chip Beads-LCB Series



Part Number	Test Freq. (MHz)	Impedance ( $\Omega \pm 25\%$ )	DC Resistance ( $\Omega$ )Max.	Rated Current (mA)Max.
LCB321616T-250K	100	25	0.10	500
LCB321616T-600K	100	60	0.20	500
LCB321616T-700K	100	70	0.20	500

Part Number	Test Freq. (MHz)	Impedance ( $\Omega \pm 25\%$ )	DC Resistance ( $\Omega$ )Max.	Rated Current (mA)Max.
LCB322513T-320K	100	32	0.20	500
LCB322513T-600K	100	60	0.20	500
LCB322513T-900K	100	90	0.20	500

Part Number	Test Freq. (MHz)	Impedance ( $\Omega \pm 25\%$ )	DC Resistance ( $\Omega$ )Max.	Rated Current (mA)Max.
LCB451616T-500K	100	50	0.20	600
LCB451616T-600K	100	60	0.20	600
LCB451616T-800K	100	80	0.20	600
LCB451616T-101K	100	100	0.30	500
LCB451616T-151K	100	150	0.30	500
LCB451616T-171K	100	170	0.30	500

Part Number	Test Freq. (MHz)	Impedance ( $\Omega \pm 25\%$ )	DC Resistance ( $\Omega$ )Max.	Rated Current (mA)Max.
LCB453215T-700K	100	70	0.30	500
LCB453215T-121K	100	120	0.30	500