


TCR series 厚膜晶片電阻



4 digit marking for E96(F)
examples: 22R1 : 22.1 Ω
1020 : 102 Ω
1542 : 15.4k Ω



3 digit marking for E96(F)
examples: 02C (Table below)
 $102 \times 10^2 = 10.2k \Omega$



15E (Table below)
 $140 \times 10^4 = 1.4M \Omega$

0603 1%, 5% Marking Table

Code	E24	E48	E96	Code	E24	E48	E96	Code	E24	E48	E96	Code	E24	E48	E96
01	100	100	100	25	180	178	178	49		316	316	73	560	562	562
02			102	26			182	50			324	74			576
03		105	105	27		187	187	51	330	332	332	75		590	590
04			107	28			191	52			340	76			604
05	110	110	110	29		196	196	53		348	348	77	620	619	619
06			113	30	200		200	54			357	78			634
07		115	115	31		205	205	55	360	365	365	79		649	649
08			118	32			210	56			374	80			665
09	120	121	121	33		215	215	57		383	383	81	680	681	681
10			124	34	220		221	58	390		392	82			698
11		127	127	35		226	226	59		402	402	83		715	715
12	130		130	36			232	60			412	84			732
13		133	133	37		237	237	61		422	422	85	750	750	750
14			137	38	240		243	62	430		432	86			768
15		140	140	39		249	249	63		442	442	87		787	787
16			143	40			255	64			453	88			806
17		147	147	41		261	261	65		464	464	89	820	825	825
18	150		150	42			267	66	470		475	90			845
19		154	154	43	270	274	274	67		487	487	91		866	866
20			158	44			280	68			499	92			887
21	160	162	162	45		287	287	69	510	511	511	93	910	909	909
22			165	46			294	70			523	94			931
23		169	169	47	300	301	301	71		536	536	95		953	953
24			174	48			309	72			549	96			976

Code	A	B	C	D	E	F	G	H	X	Y	Z
Multiplier	10^0	10^1	10^2	10^3	10^4	10^5	10^6	10^7	10^{-1}	10^{-2}	10^{-3}